


调频 / 调幅系列 陶瓷鉴频器

Ceramic Discriminator For Communication FM/AM Series

kHz CD455KHz 调幅系列 插入式陶瓷鉴频器

kHz CD455KHz Series of Ceramic Discriminatot for AM (Lead-type)



■ 特点 Feature

- ▶ 稳定性好，灵敏性高
High Stability and semsibility
- ▶ 小型化和重量轻松
Small Size and Light Weight
- ▶ 低价格和无调整性
Low Price and Non-Adjustable

尺寸(Size) : 6.0 * 6.0 * 3.0

■ 技术特性 Technicst Characteristics

型号 PART NO.	反谐振频率 Anti-resonant Freq.Fr	$\Delta F(F_a-F_r)$	谐振电阻 Resonant Resistance	电容 Static Capacitance
CD455C03	$455 \pm 1.5\text{kHz}$	$46 \pm 5.0\text{kHz}$	70 Max	$550\text{pF} \pm 20\%$

型号 PART NO.	解调3dB带宽 Demodu lation 3dB Band Width	解调 输入 Demodu lation Output (455kHz)	偏差因素 Distortion Factor (455kHz)
CD455C24	$\pm 4.0\text{kHz}$ min	$100 \pm 20\text{mv}$	2.0% max
CD455C28	$\pm 3.0\text{kHz}$ min	$40 \pm 20\text{mv}$	3.0% max
CD455C32	$\pm 4.0\text{kHz}$ min	$40 \pm 20\text{mv}$	3.0% max
CD455C40	$\pm 4.0\text{kHz}$ min	$40 \pm 20\text{mv}$	3.0% max
CD455C47	$\pm 4.0\text{kHz}$ min	$45 \pm 10\text{mv}$	3.0% max
CD455C50	$\pm 4.0\text{kHz}$ min	$64 \pm 6.4\text{mv}$	4.0% max

■ 外型尺寸 Dimension

